



AUDIO / VIDEO TRANSMITTER AND RECEIVER

REF. 7167

DIGIDOM AV 5.8 GHZ

The use of transmission systems that share the same frequency of 2.4 GHz as other electronic equipment such as microwaves or wireless networks, significantly increases the possibility of sound and image failures, since they share the same transmission channel

- 5.8GHz transmitter and receiver
- 8 selectable channels
- A/V source in (satellite, decoder, DVD player, etc.)
- Loop-through function
- Low power consumption
- IR remote control data rate: 38k

REF	DESCRIPTION	EAN 13
7167	DIGIDOM AV 5.8GHz	8424450145975

TRANSMITTER AND RECEIVER

DIGIDOM AV 5.8 GHz

A HIGH FREQUENCY OF USE MINIMIZES THE POSSIBILITY OF INTERFERENCES WITH OTHER EQUIPMENTS

FEATURES

- ✓ For situations where it is not possible to connect the TV set to any outlet of the coaxial distribution network.
- ✓ **Quick and easy-to-install** solution for access to contents (satellite receiver, set-top box, DVD player, etc..) at any point of the home **without running wires**.
- ✓ For situations where there are working more than one DIGIDOM 5.8 GHz system in the same installation or to **avoid interferences** with similar neighboring systems, you can select one out of eight different channels making use of micro-switches at the rear of the device.

TECHNICAL FEATURES

Transmitter (TX)			
Channel / Frequency	(N° / MHz)	1 / 5733	5 / 5809
		2 / 5752	6 / 5828
		3 / 5771	7 / 5847
		4 / 5790	8 / 5866
Output level	(dBm)	10	
Video Input Level	(Vpp)	1	
Audio Input Level	(Vpp)	1	
Video Input Impedance	(ohm)	75	
Audio Input Impedance	(ohm)	600	
Supply Voltage	(Vdc, 300 mA)	9	
Power Consumption	(mA)	150	
Dimension	(mm)	129 x 113 x 36	
Receiver (RX)			
Output Level A/V	(Vpp)	1	
Receiver Sensitivity	(dBm)	-85	
Supply Voltage	(Vdc, 300 mA)	9	
Power Consumption	(mA)	270	
Single-Channel IR Transmission Frequency	(MHz)	433,99	
Dimension	(mm)	129 x 113 x 36	

TYPICAL APPLICATION

