

## Smartvest Wireless Remote Control

Art.-Nr. FUBE35000A

---



- 
- Smartvest extension for operation without a mobile device
  - Immediate operation at the push of a button and with no need for a PIN code
  - Buttons for arming and disarming Smartvest
  - Panic alarm that can be triggered at the push of a button
  - Individual configuration of buttons to automatically activate additional components (cameras, sirens, etc.) simultaneously
  - Visual feedback via blue LED
  - Low battery notification sent to the Smartvest alarm control panel
  - Small, portable and easy to use
- 

In addition to the smartphone and tablet option, the Smartvest Wireless Remote Control offers you another streamlined and convenient option for operation – at the push of a button, without the need for a PIN code. With this option, you can both arm and disarm the Smartvest or, in an emergency, trigger a panic alarm at the touch of a button. Using the app, the button can also be configured so that certain cameras or the siren are activated when the buttons are pressed. The Smartvest Wireless Remote Control thus provides basic control options in a compact and handy form ensuring it is simple and intuitive to use.

# Smartvest Wireless Remote Control

Art.-Nr. FUBE35000A

## Technical Data

Battery type	1xCR2032
Certifications	CE
Display	LED
Height	60mm
Housing material	ABS
Length	14mm
Luminous color	blue
Max. battery life	2A
Max. humidity	80%
Max. operating temperature	40°C
Max. receiving range (building)	30m
Max. receiving range (outdoors)	100m

Max. sending range (building)	30m
Max. sending range (outdoors)	100m
Min. operating temperature	0°C
Modulation	FSK
Net weight	0,022kg
Power consumption	15mA
Power consumption Standby	0,005mA
Radio frequency	868MHz
Tamper monitoring	No
Width	30mm