

Smartvest Wireless Siren

Art.-Nr. FUSG35000A



-
- Smartvest extension for sounding alarms indoors and outdoors
 - Quick and cable-free installation without the need for wires thanks to battery operation
 - High-volume siren (up to 100 dB) and red LED strobe light for alarms with deterrent effect
 - Sturdy, weatherproof siren (IP44)
 - Automatic supervision, with functional tests repeated daily and feedback sent to the Smartvest alarm control panel
 - Low battery notification sent to the Smartvest alarm control panel
 - Battery life of up to 2 years
 - Tamper protection provided by anti-removal wall contact
-

To be able to provide alarming both indoors and outdoors, the Smartvest Wireless Siren is fitted with a loud siren (up to 100dB) and a red LED strobe light. Battery operation (battery life: up to two years) means no wiring is required during installation; when the battery is low, the alarm panel is notified immediately. To be able to guarantee real security, the Smartvest Wireless Siren is fitted with tamper protection in the form of an anti-removal wall contact.

Smartvest Wireless Siren

Art.-Nr. FUSG35000A

Technical Data

| | |
|----------------------------|----------|
| Battery type | 4 x C |
| Certifications | CE |
| DC voltage supply | 5V |
| Height | 300mm |
| Housing material | ABS |
| IP protection class | 44 |
| Illuminant | LED |
| Installation location | Outdoors |
| Length | 102mm |
| Luminous color | Red |
| Max. humidity | 80% |
| Max. operating temperature | 50°C |

| | |
|---------------------------------|--------|
| Max. receiving range (building) | 30m |
| Max. sending range (building) | 30m |
| Min. operating temperature | -10°C |
| Modulation | FSK |
| Net weight | 0,87kg |
| Power consumption | 200mA |
| Radio frequency | 868MHz |
| Sound pressure | 100dB |
| Width | 112mm |