

## Smartvest Wireless-Keypad

Art.-Nr. FUBE35010A

---



- 
- For arming/disarming the control panel
  - Integrated proximity chip key reader
  - Panic alarm which can be triggered at any time
  - Tamper alarm for unauthorised removal and/or manipulation of the control device
  - Illuminated touchpad
  - Power supply via batteries and/or external power supply
- 

### Convenient operation via code or proximity chip

The Smartvest wireless control panel is an easy-to-use operating unit for the Smartvest wireless alarm system, which enables the user to arm (including internally when people are inside), disarm and trigger a panic alarm. Alarms can be disarmed by entering a code or thanks to the built-in proximity chip reader via RFID chips, in which case there is no need to input a code at all. Up to 8 RFID chips can be paired in total and then attached to everyday objects (e.g. your wallet or keys).

### A clever design with eye-catching lights

Operation of the touchpad is visible due to the backlit interface, ensuring ease of use and an attractive appearance. Power can be supplied by connecting a power supply unit via the socket or by using batteries – both options are included within the scope of delivery.

## Smartvest Wireless-Keypad

Art.-Nr. FUBE35010A

### Technical Data

Certifications	CE
Display	LED
Height	140mm
Housing material	ABS
Length	35mm
Max. battery life	1year(s)
Max. operating temperature	40°C
Max. receiving range (building)	30m
Max. receiving range (outdoors)	100m
Max. sending range (building)	30m
Max. sending range (outdoors)	100m

Min. operating temperature	0°C
Modulation	FSK
Net weight	0,305kg
Power consumption	2,1mA
Power consumption Standby	0,1mA
Radio frequency	868MHz
Tamper monitoring	nein
Type of reader	125 kHz
Width	120mm